


Hexalobular Socket Truss Head Screws







Material/Finish



| | SNMXS | | | | | | |
|----------|-------------------------------|--|--|--|--|--|--|
| Material | SUSXM7 (Equivalent to SUS304) | | | | | | |

Application

Prevention of damage to screw heads Reliable tightening



- Hexalobular socket shapes*1 are designed to withstand high tightening torque compared to cross-recesses.
- Recesses are unlikely to be damaged due to tightening, allowing safe and secure tightening to be performed.
- *1: The hexalobular shape is prescribed by JIS B 1015: 2008(ISO 10664: 2005)"Hexalobular internal driving feature for bolts and screws".

Unit:mm

| Part Number 1 | M (Coarse) | | | L 42 | | | | | | | D. | | Hexalobular | Mass (g) | Oty per Book |
|---------------|-------------------|-------|-----|-------------|----|----|----|----|----|----|----------------|-----|-------------|-------------|--------------|
| | Nominal of Thread | Pitch | L Z | | | | | | | | D ₁ | L1 | Socket No. | Mass (g) | Qty per Pack |
| SNMXS-M3 | M3 | 0.5 | 6 | 8 | 10 | 12 | | | | | 6.9 | 1.9 | 10 | 0.58 - 0.82 | 20 |
| SNMXS-M4 | M4 | 0.7 | 6 | 8 | 10 | 12 | 16 | 20 | | | 9.4 | 2.5 | 20 | 1.4 - 2.5 | 20 |
| SNMXS-M5 | M5 | 0.8 | | 8 | 10 | 12 | 16 | 20 | | | 11.8 | 3.1 | 25 | 2.9 - 4.3 | 20 |
| SNMXS-M6 | M6 | 1 | | | 10 | 12 | 16 | 20 | 25 | 30 | 14 | 3.7 | 30 | 5.2 - 8.7 | 20 |
| SNMXS-M8 | M8 | 1.25 | | | | | 16 | 20 | 25 | 30 | 17.8 | 4.8 | 40 | 13 - 17 | 20 |

• When purchasing less volume than one full bag, a separate handling fee is charged. For details, see the Sold Separately Service.

Related Products

SKX Hexalobular Wrench



SKX-N Hexalobular Wrench for **Extremely Limited Access** Spaces



SKXB Hexalobular Short Bit



SRD Magnet Screwdriver




• Part Number Specification



1 Individual Sales Available / Add'l charge | Available / Add'l charge

🕵 Cleanroom Wash & Packaging 🞳 Screw Length Adjustment 💶 Vibration Resistant 📔 Modification process for captive use



Available / Add'l charge | Available / Add'l charge | Available / Add'l charge

